

MIX-8S STEREO LINE MIXER



The MIX-8S provides 8 stereo balanced line level inputs in an economical, space-saving package for broadcast audio mix-minus and studio monitoring of multiple stereo feeds. Each channel has a front-panel volume control, with a single master volume control for the stereo output level. The unit also includes a headphone volume control and headphone jack for monitoring the stereo program mix. The stereo inputs and outputs are balanced or unbalanced line level via TRS 1/4" jacks.

Frequency Response: 30Hz-20kHz ± 0.5 dB
Maximum Input Level: +22dBu
Input Impedance: 10k Ohms
Maximum Output Level: +22dBu
Output Impedance: 100 Ohms
Rise Time: 5 μ S
Total Harmonic Distortion: 0.05%
Power Requirements: 115/230VAC
Gain Structure:
 Channel Gain: 18dB
 Master Gain: 18dB
 Total Gain: 36dB
Headphone Impedance: 30 Ohms minimum